



# ***KNG Handheld Control Head***

## ***KAA0670 User's Guide***





**Many factors are taken into consideration when implementing features and functionality of KNG Series transceivers. Ease of use and customer requirements are among the most important to us. Most enhancements are achieved thru firmware updates.**

**Current firmware and editor versions, along with the latest user manuals and addendums, are available for download in the support section of the BK Technologies web site.**

**We recommend joining our e-mail list to keep informed of updates and enhancements on all your BK Technologies and BK Radio products.**

**Visit us at:  
[www.bktechnologies.com](http://www.bktechnologies.com)**



# Contents

<b>Introduction .....</b>	<b>1</b>
<b>FCC Requirements.....</b>	<b>2</b>
<b>Information and Installation Options .....</b>	<b>8</b>
<b>Handheld Control Head Controls.....</b>	<b>10</b>
<b>LCD Touch Screen .....</b>	<b>13</b>
Status Indicators .....	14
Channel Information Display Options .....	16
Programmable Button and Menu Options .....	18
<b>Function Selection.....</b>	<b>23</b>
Touch Screen Selection .....	23
Navigation Wheel Selection .....	24
Menu Screen Selection .....	25
Exiting the Menu .....	26
<b>Channel/Zone Selection Options .....</b>	<b>27</b>

<b>Basic Operation .....</b>	<b>28</b>
<b>Trunking Channel Basic Operation .....</b>	<b>30</b>
<b>Command Zone Operation .....</b>	<b>32</b>
Building a Command Zone [CHAN+].....	32
Editing a Command Zone [CHAN-] .....	33
<b>Code Guard/NAC Operation .....</b>	<b>34</b>
Code Guard Receive .....	34
Code Guard Transmit .....	34
Analog Squelch Control.....	35
APCO Project 25 Digital Squelch Control .....	35
<b>Mixed Mode Operation .....</b>	<b>37</b>
<b>Scan Options.....</b>	<b>39</b>
Channel Scan [SCAN] .....	39
Channel Scan List [SCN+] .....	40
Talkback Scan.....	41
Dual Mode Scan [DSCN].....	41
Dual Mode Scan List [DSED] .....	42

Priority Scan/System Scan [PSCN].....	42
Priority Channel Select [PRI].....	43
Vote Scan.....	45
Zone Scan [ZSCN].....	46
Zone Scan List [ZSC+].....	46
<b>Encryption Operation.....</b>	<b>48</b>
Required Setup.....	48
Transmit Encryption Key Selection [KEY] .....	50
Encryption Keyset Selection [KEYST].....	50
Rekey Request [RKEY] .....	51
Keyset Viewing and Selecting [KSET].....	52
Zeroizing [ZERO].....	52
<b>User Pick List Options.....</b>	<b>53</b>
TX/RX CxCSS Picklist [TXCG] [RXCG].....	54
TX/RX Network Access Code Picklist [TNAC] [RNAC] .....	54
Talk Group ID Picklist [TGID].....	55
Encryption Key Picklist [KEY].....	55

Keyset Picklist [KSET] .....	56
<b>Emergency Signaling .....</b>	<b>57</b>
<b>Messaging Options.....</b>	<b>58</b>
Text Messaging [TXT] .....	58
User Status Messaging [STS] .....	62
<b>Paging and Call Alert.....</b>	<b>65</b>
Conventional Two-Tone/DTMF/MDC1200 Paging [MUTE] .....	65
Call Alert Paging [ALRT] .....	66
Radio Check [RCHK] .....	67
<b>Other Functions &amp; Options.....</b>	<b>69</b>
Backlight [LITE].....	69
Cloning.....	70
Control Lockout [LOCK].....	70
Global Positioning [GPS] .....	72
Inhibit/Uninhibit [INH]/UINH.....	73
Keypad Programming .....	75
Monitor [MON] .....	76

Nuisance Channel Delete [NUIS] .....	76
Repeater Talkaround [T/A] .....	77
Squelch Adjust [SQL] .....	77
Surveillance Mode [SURV] .....	78
Transmit Digital [TXD] .....	78
Transmit Power [PWR] .....	79
Versions .....	80
Zone Select [ZONE] .....	81
<b>Keypad Programming Options .....</b>	<b>82</b>
Entering Programming Mode .....	82
Keypad Programming .....	83
Code Guard Picklist Programming .....	111
NAC Picklist Programming .....	113
Talkgroup ID Picklist Programming .....	114



## **Introduction**

---

Congratulations on your purchase of the BK Radio KNG Handheld Control Head from BK Technologies.

The KNG Handheld Control Head offers an array of programmable functionality to help radio users get the most out of their portable communications. Check with your BK Radio dealer or communications officer for information on the programmed functions of your transceiver prior to operation.

This manual contains information concerning the operation procedures for the BK Radio HCH connected to a KNG Mobile transceiver. The HCH has been designed to meet the tough requirements of today's communications environment. Please take a moment to read the information in this manual so you can get optimum performance from your new Handheld Control Head.

### FCC Requirements

---

Your transceiver must be properly licensed by the Federal Communications Commission prior to use. Your BK Radio dealer can assist you in meeting these requirements. Your dealer will program each transceiver with your authorized frequencies, signaling codes, etc., and will be there to meet your communications needs as your system expands.

**NOTICE:** Effective January 1, 2013, private land mobile radios operating in the bands 150-174 MHz and 421-470 MHz must restrict effective transmitted bandwidth to 12.5 KHz (narrowband). Exceptions are allowed for marine and weather bands, and for explicitly-granted waivers from the FCC.

The KNG radio will operate in wideband mode only if the Tx frequency falls within the excepted bands, or if the user has selected the "Override Narrowbanding" option. This option can be legitimately elected only with FCC approval.

### Safety Precautions



- Do not operate the transmitter in close proximity to blasting caps.
- Do not operate the transceiver in an explosive atmosphere (petroleum fuels, solvents, dust, etc.).
- Do not operate the transmitter if a person outside the vehicle is less than three feet from the antenna or touching the antenna.

---

**RF ENERGY EXPOSURE AWARENESS AND CONTROL INFORMATION,  
AND OPERATIONAL INSTRUCTIONS FOR FCC OCCUPATIONAL USE  
REQUIREMENTS**

---

BEFORE USING YOUR MOBILE 2-WAY TRANSCEIVER, READ THE INFORMATION BELOW WHICH CONTAINS IMPORTANT OPERATING INSTRUCTIONS FOR SAFE USAGE AND RF ENERGY AWARENESS AND CONTROL INFORMATION FOR COMPLIANCE WITH RF ENERGY EXPOSURE WHERE APPLICABLE.

## **National and International Standards**

*NOTICE: This transceiver is intended for use in occupational/controlled conditions, where users have full knowledge of their exposure and can exercise control over their exposure to meet FCC limits. This transceiver device is NOT authorized for general population, consumer, or any other use.*

This 2-way transceiver uses electromagnetic energy in the radio frequency (RF) spectrum to provide communications between two or more users over a distance. It uses radio frequency (RF) energy or radio waves to send and receive calls. RF energy is one form of electromagnetic energy; other forms include, but are not limited to, sunlight and x-rays. RF energy, however, should not be confused with these other forms of electromagnetic energy, which when used improperly, can cause biological

## ***KNG HCH Operation***

damage. Very high levels of x-rays, for example, can damage tissues and genetic material.

Experts in science, engineering, medicine, health and industry work with organizations to develop standards for exposure to RF energy. These standards provide recommended levels of RF exposure for both workers and the general public. These recommended RF exposure levels include substantial margins of protection. All 2-way transceivers are designed, manufactured, and tested to ensure they meet government established RF exposure levels. In addition, manufacturers also recommend specific operating instructions to users of 2-way transceivers.

These instructions are important because they inform users about RF energy exposure and provide simple procedures on how to control it. Please refer to the following websites for more information on what RF energy exposure is and how to control your exposure to assure compliance with established RF exposure limits.

<http://www.fcc.gov/oet/rfsafety/rf-faqs.html>

<http://www.osha.gov/SLTC/radiofrequencyradiation/index.html>

## **Federal Communications Commission Regulations**

The FCC rules require manufacturers to comply with the FCC RF energy exposure limits for mobile 2-way transceivers before they can be marketed in the U.S. When 2-way transceivers are used as a consequence of employment, the FCC requires

users to be fully aware of and able to control their exposure to meet occupational requirements. Exposure awareness can be facilitated by the use of a product label directing users to specific user awareness information. Your BK Radio 2-way transceiver has an RF exposure product label. Also, your BK Radio owner's and service manuals include information and operating instructions required to control your RF exposure and to satisfy compliance requirements.

## **Compliance with RF Exposure Standards**

Your BK Radio 2-way transceiver is designed and tested to comply with a number of national and international standards and guidelines (listed below) for human exposure to radio frequency electromagnetic energy. This transceiver complies with the IEEE and ICNIRP exposure limits for occupational/controlled RF exposure environment at operating duty factors of up to 50% talk-50% listen and is authorized by the FCC for occupational use only. In terms of measuring RF energy for compliance with the FCC exposure guidelines, your transceiver antenna radiates measurable RF energy only while it is transmitting (during talking), not when it is receiving (listening) or in Standby Mode.

Your BK Radio 2-way transceiver complies with the following RF energy exposure standards and guidelines:

United States Federal Communications Commission, Code of Federal Regulations; 47 CFR §§ 1.1307, 1.1310, 2.1091 and 2.1093

## ***KNG HCH Operation***

American National Standards Institute (ANSI) / Institute of Electrical and Electronic Engineers (IEEE) C95. 1-1992

Institute of Electrical and Electronic Engineers (IEEE) C95.1-1999 Edition

## **Industry Canada Compliance**

This Class B digital apparatus complies with Canadian ICES-003.

Cet appareil numérique de la classe B est conforme à la norme NMB-003 Canada.

## **RF Exposure Compliance and Control Guidelines**

To control exposure to yourself and others and to ensure compliance with the RF exposure limits, always adhere to the following procedures.

Guidelines:

- User awareness instructions must accompany device when transferred to other users.
- Do not use this device if the operational requirements described herein are not met.

## **Operating Instructions:**

Transmit no more than the rated duty factor of 50% of the time. To transmit (talk), push the Push-To-Talk (PTT) button. The red LED will illuminate when the transceiver

is transmitting. To receive calls, release the PTT button. The red LED will extinguish when the transceiver stops transmitting. Transmitting 50% of the time, or less, is important because this transceiver generates measurable RF energy exposure only when transmitting (in terms of measuring for standards compliance).

Transmit only when persons around the vehicle are at least 3 feet (90 centimeters) away from the vehicle with a properly installed antenna. This separation distance will ensure that there is sufficient distance from a properly installed (according to installation instructions) externally-mounted antenna to satisfy the RF exposure requirements in the standards listed above.

The AMBE® voice compression software included in this product is protected by intellectual property rights including patent rights, copyrights and trade secrets of Digital Voice Systems, Inc. The user of this software is explicitly prohibited from attempting to decompile, reverse engineer, or disassemble the object code, or in any other way convert the object code into a human-readable form. This software is licensed solely for use within this product. US Patent Nos. #6,912,495 B2, #5,870,405, #5,826,222, #5,754,974, #5,715,365, #5,701,390, #5,649,050, #5,630,011, #5,581,656, #5,517,511, #5,491,772, #5,247,579, #5,226,084, and #5,195,166.

## **Contact Information**

For additional information on exposure requirements or other information, visit website <http://www.bktechnologies.com>.

# Information and Installation Options

---

Depending on model type, KNG transceivers operate in the VHF, UHF or 800MHz frequency band. Up to 2048 channels can be programmed into the transceiver. The channels may be divided into operating zones.

Zones can be designated as standard operating zones or command zones. Command zones are made of up of channels selected from standard operating zones.

## Models

Model	Frequency
M150(LP)	136 - 174Mhz
M400	380 - 470Mhz
M500	440 - 520HMz
M800	763 - 870Mhz

**Note:** The Handheld Control Head (KAA0670) can operate with all frequency bands.


## Installation Options

There are several installation options for the KNG Mobile and Remote Mount. Please refer to the installation instructions provided with the HCH for more detailed installation information.

Installation Type	KNG-Mxxx	KNG-MxxxR
<b>Cab Mount</b>	KAA0639C	KAA0639C
<b>Trunk Mount</b>	KAA0639 and KAA0635 (8ft) or KAA0636 (17ft) or KAA0637 (25ft)	KAA0639 and KAA0635 (8ft) or KAA0636 (17ft) or KAA0637 (25ft)

**Note:** If two Handheld Control Heads are to be installed, each HCH must be programmed to the specific port that it is connected to. With the HCH powered down, power on the HCH while holding the home button. Select "Control Head Address" from the menu and select the appropriate port number.

## Handheld Control Head Controls



**On / Off:** Pushing the button in and releasing will toggle the state of the HCH from on to off and back.

**USB Port:** This is a USB client port and is used for programming and configuring the radio with the Windows PC programming software.

**LCD Touch Screen:** The LCD screen is used to show radio status and operating condition as well as receive input from the user via programmed buttons. Up to three lines of information can be displayed in the main display window. (See Display Options)

**PTT:** Press and hold the PTT (Push-To-Talk) switch on the microphone to transmit.

**LED:** The LED indicator is used to show various operational states such as active receive and active transmit.

**Microphone Element:** While transmitting, talk in a normal voice with the microphone element approximately one to two inches from your mouth.

**Channel Select:** The Channel Select buttons may be programmed via PC to select channels or zones. Use the up or down button to select the desired channel or zone.

**Volume Select:** Use the up or down button to increase or decrease the audio volume setting.

**Emergency Button:** The orange programmable function button is typically assigned to the Emergency Operation mode, but can be programmed for other functions. (See Button Options)

## ***KNG HCH Operation***

**Programmable Buttons:** Up to four touch-activated buttons and two physical top buttons (orange and black) can be programmed. (See Button Options)

**Menu Navigation:** The menu navigation pad is used to navigate the menu system. Use the up/down/right/left buttons to highlight a menu selection. Press OK to select the currently highlighted menu item.

**Home:** Pressing the Home button returns the radio to the programmed home channel. When navigating a menu, pressing the Home button will exit the menu mode and return to normal radio operation.

## LCD Touch Screen

KNG Handheld Control Heads are equipped with a programmable touch sensitive display.

The bottom line of the display is populated with programmable buttons. Button functions are assigned using the PC radio editor. Buttons are toggled off or on by pressing the displayed icon.

The top line displays radio activity such as transmit and receive indications, scan operations, etc.


The middle section shows programmed information for the selected channel.

(See Channel Information Display Options)




Status Indicators

Programmable Channel  
Information









Programmable Buttons



## Status Indicators

	Receiver Signal Strength
<b>RXD, RXA</b>	Receive Digital, Receive Analog, Hold Time Active
<b>TXD, TXA</b>	Transmit Digital, Transmit Analog
<b>H</b>	High Transmit Power
<b>L</b>	Low Transmit Power
<b>P1, P2</b>	Priority 1 Channel, Priority 2 Channel
	Selected channel is encrypted. Flashing when Rx incoming signal is encrypted
	Scanned Channel

(continued)

Status Indicators	
	Channel Scan On
	Zone Scan On
	Priority Scan On
	Dual Mode Scan On
	Repeater Talkaround Enabled
	Monitor Mode
	Open Audio
	Voice Mute Enabled

## Channel Information Display Options

NOTE: Three channel information lines are programmable with PC Radio Editor. Displayed information in conventional mode may differ from trunked channels.

<b>Channel Label</b>	Channel Label of Currently Selected Channel or Active Scanned Channel
<b>Channel Number</b>	Channel Number of Currently Selected Channel or Active Scanned Channel
<b>Channel Number and Zone Label</b>	Currently Selected Channel number and Currently Selected Zone Label
<b>Frequency</b>	Operating Frequency of Currently Selected Channel or Active Scanned Channel
<b>Unit ID</b>	<p>Shows your P25 Unit ID</p> <p>While receiving, the ID of the radio transmitting the message is displayed</p> <p>If the received ID is programmed in your radio's Call List, the corresponding label will be displayed</p>
<b>Received Talk Group ID</b>	P25 Talk Group ID of the radio transmitting the message currently being received

(continued)

## Channel Information Display Options (cont.)

<b>Pick List Selection*</b>	NAC, TGID or Code Guard currently selected from the programmable Pick Lists
<b>Zone Label</b>	Label of Currently Selected Zone
<b>Zone # and Channel #</b>	Currently Selected Zone and Channel Numbers
<b>Zone Number</b>	Currently Selected Zone Number
<b>RX/TX Key</b>	Currently selected encryption key
<b>Subaudible*</b>	Displays CxCSS value of received signal
<b>DTMF*</b>	Displays the DTMF tones of received signal
<b>MDC*</b>	Displays the MDC ID of received signal
*Conventional Channels Only	

## Programmable Button and Menu Options

NOTE: Active functions are indicated by highlighted text.

**SCAN** = Active, **SCAN** = Inactive.

	Menu	Button	Label	Trunk	Conv
Auxiliary 1/2/3	X	X	AUX1/2/3	X	X
Backlight	X	X	LITE	X	X
Call Alert	X	X	ALRT	X	X
Channel Add/Delete		X	CHAN+/-		X
Channel Scan	X	X	SCAN		X
Channel Scan List	X	X	SCN+		X
Channel Select	X	X	CHAN	X	X
Cloning	X		-		X
Control Lock	X	X	LCK	X	X
Dual Mode Scan	X	X	DSCN	X	X

<b>Programmable Button and Menu Options (cont)</b>					
	<b>Menu</b>	<b>Button</b>	<b>Label</b>	<b>Trunk</b>	<b>Conv</b>
<b>Dual Mode Scan List</b>	X	X	<b>DSED</b>	X	X
<b>Emergency<sup>1</sup></b>		X	<b>-</b>	X	X
<b>GPS</b>	X	X	<b>GPS</b>	X	X
<b>Home Channel</b>		X	<b>HOME</b>	X	X
<b>Inhibit</b>	X	X	<b>INH</b>		X
<b>Keypad Programming</b>	X		<b>-</b>		X
<b>Monitor</b>	X	X	<b>MON</b>		X
<b>Nuisance Delete</b>		X	<b>DEL</b>		X
<b>Picklist - Rx CxCSS</b>	X	X	<b>RXCG</b>		X
<b>Picklist - Rx NAC</b>	X	X	<b>RXNC</b>		X
<b>Picklist - Talkgroup ID</b>	X	X	<b>TGID</b>		X

(cont.)

## Programmable Button and Menu Options (cont)

	Menu	Button	Label	Trunk	Conv
Picklist - Tx CxCSS	X	X	TXCG		X
Picklist - Tx NAC	X	X	TXNC		X
Picklist-KEY*	X	X	KEY		X
Picklist-KEYSET**	X	X	KSET	X	X
Priority Channel	X	X	PRI		X
Priority Scan	X	X	PSCN	X	X
Radio Check	X	X	RCHK		X
Radio Info	X		-	X	X
Rekey Request**	X	X	RKEY	X	X
Repeater Talkaround***	X	X	T/A		X
Site Display****	X	X	STDS	X	

(cont.)

<b>Programmable Button and Menu Options (cont)</b>					
	<b>Menu</b>	<b>Button</b>	<b>Label</b>	<b>Trunk</b>	<b>Conv</b>
<b>Site Lock****</b>	X	X	<b>STLK</b>	X	
<b>Site Search****</b>	X	X	<b>STSR</b>	X	
<b>Squelch Adjust</b>	X	X	<b>SQL</b>		X
<b>Surveillance Mode</b>	X	X	<b>SURV</b>	X	X
<b>Text Message</b>	X	X	<b>TXT</b>		X
<b>Tx Digital/Analog</b>	X	X	<b>TXAD</b>		X
<b>Tx Power</b>	X	X	<b>PWR</b>	X	X
<b>Tx Secure*</b>	X	X	<b>SEC</b>	X	X
<b>Unihabit</b>	X	X	<b>UNINH</b>		X
<b>Unit Call</b>	X	X	<b>UNIT</b>	X	X
<b>User Status</b>	X	X	<b>STS</b>		X

(cont.)

<b>Programmable Button and Menu Options (cont)</b>					
	<b>Menu</b>	<b>Button</b>	<b>Label</b>	<b>Trunk</b>	<b>Conv</b>
<b>Version</b>	X		-	X	X
<b>Voice Mute***</b>	X	X	<b>MUTE</b>		X
<b>Zeroize Keys*</b>	X	X	<b>ZERO</b>	X	X
<b>Zone Scan</b>	X	X	<b>ZSCN</b>		X
<b>Zone Scan List</b>	X	X	<b>ZSC+</b>		X
<b>Zone Select</b>	X	X	<b>ZONE</b>	X	X

<sup>1</sup>Emergency function can only be assigned to the orange button.

\*Requires Encryption option.

\*\* Requires Encryption and OTAR options.

\*\*\*Works on a per-channel basis.

\*\*\*\*Requires P25 Trunking option.

---

## Function Selection

---

Most radio functions can be programmed as Touch Screen selections, top function buttons or as part of a menu list.

NOTE: Items can be directly accessed from the Touch Screen or by using the menu navigation buttons on the front of the control head.

### Touch Screen Selection

To toggle assigned Touch Screen functions on and off, or access the associated menu, press the desired function on the LCD touch screen.




### Navigation Wheel Selection

The navigation wheel on the controller front panel can also be used to toggle functions and access menu lists.


Use the right, left, up and down arrows to highlight the desired function. Press the OK button to open the menu or toggle the highlighted item.

The active button will be highlighted.




## Menu Screen Selection

A list of additional functions are accessed by pressing the "MENU" button or highlighting "MENU" with the Navigation Wheel and pressing OK.



Use the Up/Down arrows to highlight the desired function.

NOTE: The list can be automatically scrolled by holding the Up/Down buttons





## KNG HCH Operation

Use "ENTER" or "OK" to select the highlighted function.

When selected, a menu for the function will show in the display.

Use the Up/Down arrows to highlight the desired setting then "ENTER" or "OK" to select or set the function.



## Exiting the Menu

To return to normal operation press the HOME button or press and hold "ESC".



---

## **Channel/Zone Selection Options**

---

The HCH can be programmed with up to 2048 individual channels. These channels can be divided into zones of one or more channels. Accessing a channel or zone depends on radio programming.

Channels or zones can be selected using the channel/zone select buttons or by an assigned button or menu item. More than one selection mode can be programmed.

### **Channel/Zone Selector Buttons**

When programmed with the default setting, the channel select buttons are used to select a channel from the active zone. If programmed to select zones, zones will be selected with the buttons.

### **Button/Menu Item Selection**

If programmed to a button, pressing the button will display the list of available channels or zones. If programmed as a menu item, the lists can be displayed by selecting Zone Select or Channel Select from the menu list.

Use the Up/Down buttons to scroll to the desired selection. Press "ENT" or "OK" to go to the highlighted zone or channel.

## **Basic Operation**

---

### **Receive**

1. Turn power on by pushing and releasing the On/Off button. The HCH will beep, indicating that it has passed its self test and is operational.
2. Set volume by pressing and holding the [MON] button, to hear squelch noise or by selecting "Monitor Mode" from the menu list and selecting "Open" . Press the up or down volume select buttons to set a comfortable volume level. Press the [MON] button again or select desired monitor mode from the "Monitor Mode" menu to stop squelch noise.
3. Select a channel zone (if applicable) by pressing the [ZONE] button or selecting "Zone Select" from the menu and scrolling to the desired zone. Press the "OK" button to return to Channel Select mode.
4. Select a channel by pressing the up or down channel select buttons. When selecting a channel above the highest channel, the radio will return to the lowest channel. When selecting below the lowest (1st) channel, the radio will go to the highest channel.

## **Transmit**

1. To transmit, Press the PTT (Push-To-Talk) switch on the HCH. The TX annunciator appears on the display and the red Transmit indicator illuminates while the PTT is pressed.
2. Talk in a normal voice with the microphone element approximately one to two inches from your mouth.
3. Release the PTT switch to stop transmitting.
4. If the TX annunciator does not appear and a tone is heard, you are on a receive-only channel or the channel is busy and Busy Channel Lockout is enabled. Use the channel select buttons to select an authorized transmit channel or wait until the channel is clear.
5. If the length of your transmission exceeds the preset Time-Out Timer setting, the transmitter automatically shuts off and a tone sounds. To continue the transmission, release the PTT switch, then press it again and continue talking.

## **Trunking Channel Basic Operation**

---

Some KNG transceivers are equipped with optional P25 Trunking capability. Trunking parameters and functions can only be programmed by qualified persons via PC. Contact your system administrator or radio dealer for information on how your radio is programmed.

### **System Registration**

If the radio is powered on when a trunking channel is selected, the radio will attempt to register with the selected trunking system.

The LED will flash twice upon successfully registering with the system and setting talkgroup affiliation.

If the affiliation was unsuccessful, the LED will continue to flash.

If the radio is not in range of the system, "Out of Range" will be displayed and an alert tone will sound every ten seconds.

If registration is refused or denied, a denied message and tone will appear briefly before switching to "Out of Range" mode.

After successful registration the programmed LCD display criteria is displayed.

## **Transmitting**

When the PTT is pressed, a three beep Talk Permit Tone will be heard if the channel is available.

If there is no channel available the radio will emit a tone and display "BUSY".  
Release the PTT.

The radio will remain in busy mode until the channel is available.

When the channel becomes available the three beep Talk Permit Tone will be emitted. Re-press the PTT to continue your call.

If the PTT is not pressed within two seconds of the Talk Permit Tone, the radio will return to normal standby mode.

## **Command Zone Operation**

---

The KNG HCH allows construction of Command Zones drawn from any of the programmed channels in standard operating zones. Each zone is designated as a Standard Operating Zone or a Command Zone with the PC radio editor software.

### **Building a Command Zone [CHAN+]**

To build a Command Zone, the “Channel Add/Delete” function must be assigned to a programmable button.

While operating in a standard zone press the “CHAN+” button to add the currently selected channel to a command zone.

The list of available command zones will be displayed. Use the up/down arrows to select the zone to add the channel.

Pressing the “Enter” button copies the channel information to the first available channel slot in the selected command zone.

Example: If the command zone has three channels, the newly added channel will be channel four.

## **Editing a Command Zone [CHAN-]**

When operating in a Command Zone, press the “CHAN-” button to remove the selected channel from the zone.

When a channel is deleted, the display momentarily shows “Channel Deleted”, and the following channels move up in the list. For example, if channel 5 is deleted, channel 6 becomes the new channel 5, channel 7 becomes the new channel 6, etc.

Press and hold the “CHAN-” button to remove all channels in the selected command zone.

**NOTE:** Modifications to a command zone channel, such as User Selected Tones, do not affect the original standard zone channel. Also, modifications to the original standard zone channel do not affect the command zone channel.

## **Code Guard/NAC Operation**

---

### *Conventional Channels*

#### **Code Guard Receive**

Analog channels programmed with a receive code guard will be heard only when the proper carrier frequency and Code Guard value is received. When the transceiver is in monitor mode, analog and mixed mode receive channels will also unmute even without the proper Code Guard being received.

#### **Code Guard Transmit**

Whenever transmitting on an analog channel, any programmed sub-audible Code Guard is transmitted. Depending on radio programming, the Code Guard can be the default tone assigned to the channel or a tone selected from the Code Guard Picklist. (See Pick List Options.)

The frequency must be clear prior to transmitting on a Code Guarded channel. If the LED Indicator is blinking green, do not transmit. Busy Channel Lockout can be programmed to disallow transmitting while a channel is busy.

1. Press the PTT switch.

When the transmitter is on, the LED Indicator glows red and TX appears in the display.

2. Talk in a normal voice with the microphone element one to two inches from your mouth.
3. Release the PTT switch to stop transmitting.

## **Analog Squelch Control**

Sub-audible signaling (CTCSS/CDCSS) is used to allow a group of radios to be selectively called in an analog system. Programming the receive code guard equal to zero turns off this feature while receiving, and allows for Carrier Squelch operation, where the radio will unmute whenever a carrier is detected regardless of the transmitted Code Guard.

## **APCO Project 25 Digital Squelch Control**

Network Access Codes (NACs) provide the digital equivalent of analog sub-audible signaling (CTCSS/CDCSS), allowing a group of radios to be selectively called within a system.

Users in the same area (using the same NAC) can be further divided into Talk Groups, with each group having its own Talk Group ID (TGID). Group Calls are made by designating both the users' NAC and TGID.

Each radio also has an individual P25 unit ID. A Unit-to-Unit call contains the addressee's NAC, and uses the addressee's P25 unit ID instead of the TGID.

## ***KNG HCH Operation***

When operating in Digital Mode, each channel can be programmed to use either Normal squelch or Selective squelch.

Normal squelch is used to mimic analog operation. Signals are only qualified with the programmed NAC. TGIDs and P25 Unit IDs are ignored. Each digital channel is programmed with a receive NAC and a transmit NAC. When an incoming signal's NAC matches the channel's programmed receive NAC, the radio unmutes. The default NAC is 293 (0659 decimal).

The digital equivalent of carrier squelch is achieved by programming the receive NAC = F7E (3966 decimal). The radio will unmute when a digital signal with any NAC is detected. The F7E (3966 decimal) NAC is reserved for receivers and is not allowed as a transmit NAC.

Selective squelch is used for processing Group Calls and Unit-to-Unit Calls. TGIDs are assigned on a per-channel basis. Users can be separated into Talk Groups with each group having its own TGID. Then, on channels programmed for Selective squelch, the incoming signal's NAC and TGID must match the channel's programmed receive NAC and TGID for the radio to unmute. The default TGID is 1.

The TGID value FFFF (65535 decimal) is used to effect an "All Call". If the radio receives a signal with a matching NAC and the TGID = FFFF (65535 decimal), it will unmute. Also, if the radio's programmed TGID is FFFF (65535 decimal), it will open on any signal with a matching NAC, ignoring the incoming TGID. A TGID = 0 means "no one". If the radio is programmed with the TGID = 0, it will accept incoming group calls containing the "All Call" TGID, and correctly addressed Unit-to-Unit calls only.

## Mixed Mode Operation

### Conventional Channels

The receiver and transmitter are capable of operating in analog wide-band (25 kHz channel spacing), analog narrow-band (12.5 kHz channel spacing) and APCO Project 25 Digital Mode.

Each channel's Receive and Transmit Mode can be set independently as follows:

Mode	RX	TX
<b>Analog</b>	Receive qualified analog signals only	Transmit analog signals only
<b>Digital</b>	Receive qualified digital signals only	Transmit digital signals only
<b>Mixed</b>	Automatically receive qualified analog or digital signals	Transmit analog or digital signal, depending on the status of "TX Digital" switch



Digital receptions and transmissions will be indicated by illuminating the D annunciator in addition to the RX or TX annunciator.

Analog receptions and transmissions will be indicated by illuminating the A annunciator in addition to the RX or TX annunciator.

### **Mixed Mode Talkback**

If Mixed Mode Talkback is enabled, transmissions initiated while hold time remains will be in the same mode as the received signal. Depending on programming, the RTX channel can be the main channel, a held scan or priority channel if Talkback Scan is enabled, or the Priority 1 channel if “TX on PR1” is enabled. TX Mode on the RTX channel must be set to MIXED.



Press the PTT while the RX  
indicator is shown

Mixed Mode Talkback transmissions will be in the same mode as the received signal, regardless of the status of the TX Digital switch.

The RTX channel and receive annunciators will be displayed for the duration of the timer.

---

## Scan Options


---

### Channel Scan [SCAN]

#### *Conventional Channels*

When on, Channel Scan monitors activity on the scan list channels in the currently operating zone. Scan operates only while the radio is not transmitting.

Channels designated as scan channels are identified by the ✓ symbol at the top of the LCD display.

When Channel Scan is on, the  symbol will be shown at the top of the LCD display.

When a signal is detected on a scanned channel, scanning stops and the message is received. The received channel is displayed in place of the selected channel.

Once the signal ends, the radio continues to monitor the channel for the preset scan delay time before it resumes scanning.

Channel Scan operation can be a button or menu list item. If assigned to a button, press and hold to add or remove selected channel from the scan list.

Channel Scan may be used in conjunction with Priority Scan operation (see Priority Scan).

### Channel Scan List [SCN+]


#### Conventional Channels

The Channel Scan List allows the radio user to add or remove channels from the list of channels to be monitored while channel scanning.

Channels designated as scan channels are identified by the ✓ symbol at the top of the LCD display.

Scan List operation can be assigned as a button or menu list item.

When Channel Scan List is assigned to a button, press the button to add or remove the selected channel from the scan list.



When assigned as a menu item, open the menu and select the channel you wish to add or remove from the scan list. Press “+/-” to cycles between no scan, normal scan and vote scan. Channels in the scan list will be indicated with the ☒ symbol. Voted channels will display "(V)". Pressing "ESC" will save the selections.

In addition, normal scanned channels can be added or deleted by pressing and holding a button assigned "Scan".

- 1: Voted Channel
- 2: Normal Scan Channel
- 3: Channel not scanned

(See also, Vote Scan)

## **Talkback Scan**

### *Conventional Channels*

If your radio is programmed for Talkback Scan, pressing PTT while a channel is active or while scan delay time remains, will cause the radio to transmit on the transmit frequency of the received channel. The "RX" indicator will be shown in the display while scan delay time remains.

Talkback Scan will not work if Priority Scan is on and your radio is also programmed to transmit on the Priority 1 channel. (See Priority Scan)

## **Dual Mode Scan [DSCN]**

### *Conventional and Trunking Channels*

Dual Mode scan provides the ability to scan trunking and conventional channels simultaneously.

When Dual Mode Scan is turned on the  icon is displayed and the radio scans all channels in the dual mode scan list.

Dual Mode Scan can be assigned to a button or menu list item. For best operation, Dual Mode Scan should be assigned in both conventional and trunking global settings with the PC editor.

(See also Dual Mode Scan List)

## ***KNG HCH Operation***

### **Dual Mode Scan List [DSED]**

#### ***Conventional and Trunking Channels***

Dual Mode Scan List must be assigned as a button or menu item in order to allow user viewing or editing of the dual scan channel list.

### **Priority Scan/System Scan [PSCN]**


#### ***Conventional Channels***

Two channels can be designated as priority channels. When Priority Scan is on, these channels are monitored for incoming traffic. When a qualified signal is detected the speaker is opened to listen to the message.

If a message is detected on the channel designated as Priority 2, the radio will continue to monitor Priority 1 channel for activity. If activity is detected the radio will switch to the Priority 1 channel.

When used in conjunction with Channel Scan, the radio monitors the Priority channels and will switch from a scanned channel to the Priority channel if a qualified signal is detected.

Depending on radio setup, priority channels can be tied to the currently operating zone or can be assigned to a specific channel regardless of the operating zone.

Channels designated as Priority channels are identified by the P1 or P2 symbol at the top of the LCD display. When Priority Scan is on, the  symbol will be shown.

Priority Scan operation can be assigned as a switch, a button or a menu list item.

While Priority Scanning, Zone Scan settings are disabled.

### *Trunked Channels*

On trunked channels, the [PSCN] button is used to turn system scanning on or off.

## **Priority Channel Select [PRI]**

### *Conventional Channels*

Depending on programming, priority channels can be radio-wide (System) or zone specific (Zone). Radio-wide priority channels are monitored regardless of the current operating zone. (See Priority Scan for more details.)

When this function is enabled, the user can change the priority channels. Priority Channel Select can be assigned to a button or as a menu list item.

## **Selecting a System Priority Channel**

Open the menu and select the System Priority channel you wish to change.

Press “ENTER” to open System Priority Channel menu.

Options:

**Off** - Disables the priority channel.

**Use Main** - Uses the selected channel as the priority channel.

**Select** - Assigns a specific channel as the priority channel.

## ***KNG HCH Operation***

To assign a specific channel as a System Priority Channel, highlight “Select” and press the “ENTER” button.

The Zone selection menu will be displayed.

Highlight the zone of the desired priority channel and press the “ENTER” button.

The Channel selection menu will then be displayed.

Highlight the desired channel and press the “ENTER” button to set the priority channel.

The display will return to the main Priority Channel Select menu.

### **Selecting a Zone Priority Channel**

Open the menu and select the Zone Priority channel you wish to change.

Press “ENTER” to open Priority Channel menu.

Options:

**Off** - Disables the priority channel.

**Use Main** - Uses the selected channel as the priority channel.

**Select** - Assigns a specific channel as the priority channel.

To assign a specific channel as a Zone Priority Channel, highlight “Select” and press “ENTER”.

The Channel selection menu will be displayed.

Highlight the desired channel and press the “ENTER” button to set the priority channel.

The display will return to the main Priority Channel Select menu.

## **Vote Scan**

### *Conventional Channels*

Channels in a multicast conventional system can be added to the scan list and designated as “voted” channels. When a signal is received on a voted channel the radio checks all voted channels and selects the channel with the best signal.

If enabled, vote scanning takes place whenever the channel scan switch is on.

To edit the voted channel list, "Channel Scan List" must be assigned as a Menu item.

Open the Channel Scan List menu and select the desired channel.

Use the "+/-" button to cycle between the three states: off, scan and vote scan.

NOTE: Channel voting occurs only with Channel Scan and is disabled when Zone Scanning. Channels programmed as Vote channels are treated as normal scan list channels during Zone Scan operation.

## ***KNG HCH Operation***

### **Zone Scan [ZSCN]**

#### *Conventional Channels*

With Zone Scan enabled, the radio scans all programmed scan channels in zones designated as Zone Scan zones whenever Channel Scan is on.

NOTE: Enabling Zone Scan while Channel Scan is off does not begin the scanning process. Scan is turned on or off with the Channel Scan switch.

When Zone Scan is on (and when the Channel Scan is also on), the <sup>z</sup>Z symbol will be shown at the top of the LCD display. The icon is not displayed if only Zone Scan is on. Zone Scan operation can be a button or menu list item.

While Zone Scanning, Priority Scan settings are disabled.

If allowed, the scanned zone list can be edited by the radio user.  
(See Zone Scan List).

### **Zone Scan List [ZSC+]**

#### *Conventional Channels*

The Zone Scan List allows the radio user to add or remove zones from the list of zones to be scanned.

The Zone Scan List operation can be assigned as a button or menu list item.

When Zone Scan List is assigned to a button [ZSC+], press the button to add or remove the currently operating zone from the scan list.

When assigned as a menu item, open the menu and select the Zone you wish to add or remove from the scan list. Press "+/-" to add or remove. Zones in the scan list will be indicated with the ☒ symbol.

Pressing "ESC" does not abandon changes.

## **Scanning Code Guarded Channels**

### *Conventional Analog Channels*

When a signal is detected, scanning stops while the radio checks for the proper Code Guard value. If the signal contains the proper Code Guard value, the radio receives the message. Otherwise, the radio resumes scanning immediately.

## **Transmitting with Scan On**

The radio transmits on the channel selected by the Channel Select buttons unless Talkback Scan is enabled (see Talkback Scan) or Priority Scan is on and Transmit on Priority 1 is enabled (see Priority Scan).

## **Encryption Operation**

---

*Conventional Digital and Trunking Channels Encryption equipped transceivers only. Option KZA0576 is required for secure communications.*

The KNG may optionally be configured for Secure communication on channels operating in Digital Mode. No encryption is available for analog channels.

### **Required Setup**

Radios that have the DES/AES factory option for encryption must have encryption keys loaded with an APCO Project 25 compatible key fill device such as the Motorola KVL 3000 Plus or KVL 4000 and using a BK Radio keyloader cable. The radio can hold up to 32 AES and/or DES keys.

After loading keys in the radio, the KNG PC programming software must be used to configure the radio's key table and to assign default transmit keys to each channel.

Radios that have the OTAR factory option support Over-the-Air Rekeying of encryption keys (OTAR). The KNG PC programming software must be used to enable OTAR and to mark the channel(s) that will communicate with the Key Management Facility (KMF). In addition, the radio must have key encryption keys (used only to encrypt other keys) loaded with an APCO Project 25 compatible key fill device such as the Motorola KVL 3000 Plus or KVL 4000 and using a BK Radio keyloader cable.

## **Transmit Secure [SEC]**

When SEC is on, encrypted channels programmed for switchable encryption will transmit an encrypted signal.

NOTE: The SEC switch has no effect on channels programmed as Encrypted Only or Clear Only.

Channels in the Ready-to-Transmit Encrypted mode will display the Ø symbol on the top line of the LCD.

When receiving an encrypted signal a flashing Ø symbol will be displayed.

When transmitting or receiving an encrypted signal, the TX/RX LED will alternate blue.

Transmit Secure selection can be assigned as a touch screen button, menu list item or to a top function button.

### **Transmit Encryption Key Selection [KEY]**

The radio can hold up to 32 DES or AES encryption keys. Each channel is assigned a default key for transmit. The key can be locked to the channel, or if programming allows, a transmit key other than the default key can be selected from the transceiver's Key Pick List.

To change an encryption key, open the KEY menu.  
Programmed key labels will be displayed.

Select the desired key and press “ENTER”.

To return the key to the pre-programmed value select “Default”.

If a key is selected that has not been programmed, the transceiver will emit a three beep tone and display “Key Fail” before going to standby mode. The transceiver will not transmit but will beep and display “Key Fail” when PTT is pressed.

### **Encryption Keypset Selection [KEYST]**

*OTAR equipped transceivers only.*

Selecting a keyset from the Pick List will cause the transceiver to use encryption keys from the selected keyset. User selectable pick list access can be assigned to a button or menu list item.

To change the encryption keyset, open the KEYST menu.  
Programmed Keypset labels will be displayed.

Select the desired keyset and press “ENTER”.

## **Rekey Request [RKEY]**

*OTAR equipped transceivers only.*

On radios equipped with over-the-air rekeying (OTAR), a transceiver user can manually request an encryption rekey from the Key Management Facility (KMF).

For a radio to receive encryption keys or keysets over-the-air, the selected channel must be designated as an OTAR channel via PC programming. Refer to your PC programming documentation for more information.

To request a re-key:

Open the Rekey Request menu.

Press the “YES” button to Request Keys, or press “ESC” to cancel the operation.

If the “YES” button is pressed while on a channel that has not been marked as an OTAR channel, the radio will beep and “NON-OTAR” will appear on the display.

If a successful rekey occurs, a tone will sound, and the display will momentarily show “REKEYED”.

### **Keyset Viewing and Selecting [KSET]**

*OTAR equipped transceivers only.*

The radio can hold up to 8 encryption keysets. Only one keyset can be active at any time. The radio will receive messages encrypted with any of the keys in any of the keysets, but transmit keys can only be selected from the active keyset.

To change an encryption keyset, open the KEYST menu. Programmed keyset labels will be displayed. Select the desired keyset and press “ENTER”.

### **Zeroizing [ZERO]**

The transceiver provides a method for the user to “panic-zeroize” all encryption keys. Zeroizing removes all encryption keys from the radio, including keys used for OTAR and Tactical OTAR operation.

Zeroize can be assigned as a button or menu list item.

Open the “Zeroize Keys” menu.

Press “YES” to erase all encryption keys or “ESC” to cancel the action.

When successfully removed the “Keys Removed” message will momentarily be displayed.

---

## **User Pick List Options**

---

### *Conventional Channels*

The HCH provides users the ability to select and assign Pick List functions to specific channels. Pick List Options can be assigned to a programmed button or as menu list items.

Available Pick List options include:

- Transmit Code Guards
- Receive Code Guards
- Transmit Network Access Codes
- Receive Network Access Codes
- Talk Group IDs
- Encryption Keys (see Encryption Operation)
- Encryption Keysets (see Encryption Operation)

## ***KNG HCH Operation***

### **TX/RX CxCSS Picklist [TXCG] [RXCG]**

#### ***Conventional Analog or Mixed Mode Channels***

Selecting a CTCSS/CDCSS Code Guard from the Pick List will assign the tone to the currently select analog or mixed-mode channel.

User assigned Transmit and Receive Code Guards are selected independently.

To change a Code Guard, open the RXCG or TXCG menu, select the desired tone and press “ENTER”.

To return the tone to the pre-programmed value select “Default”.

If allowed, picklist values can be changed through keypad programming.

### **TX/RX Network Access Code Picklist [TNAC] [RNAC]**

#### ***Conventional Digital or Mixed Mode Channels***

Selecting a Network Access Code (NAC) from the Pick List will assign the NAC to the currently select digital or mixed-mode channel.

User assigned Transmit and Receive NACs are selected independently.

To change a NAC, open the RXNAC or TXNAC menu, select the desired NAC and press “ENTER”.

To return the NAC to the pre-programmed value select “Default”.

If allowed, picklist values can be changed through keypad programming.

## **Talk Group ID Picklist [TGID]**

### *Conventional Digital Channels*

Selecting a Talk Group ID from the Pick List will assign the TGID to the currently select channel. All other channels are unaffected.

Open the menu of available TGIDs.

Select the desired Talk Group ID or, to return the TGID to the pre-programmed value, select "Default".

Press "ENTER" to set the selection.

If allowed, picklist values can be changed through keypad programming.

## **Encryption Key Picklist [KEY]**

### *Digital or Mixed Mode Channels*

*Encryption equipped transceivers only. Requires option KZA0576.*

Selecting an Encryption Key from the Pick List will assign the key to all encrypted channels that do not have 'Key Lock' programmed. Locked key channels will continue to use the pre-programmed key.

(See Encryption Operation)

## ***KNG HCH Operation***

### **Keyset Picklist [KSET]**

*Digital or Mixed Mode Channels*

*OTAR equipped transceivers only. Requires option KZA0580 or KAA0580.*

Selecting a Keypset from the Pick List will cause the radio to use encryption keys from the selected Keypset.

(See Encryption Operation)

---

## **Emergency Signaling**

---

If programmed, the Orange button on the top panel is used to send an emergency call on the programmed Emergency channel. If emergency channel is assigned for digital operation, the emergency signal is broadcast using digital P25 protocol. If the assigned channel is analog, the emergency signal is broadcast using MDC protocol.

### **Sending an Emergency Call**

Press and hold the button to initiate an Emergency Call.

Once the call is activated, the emergency message is transmitted automatically based on radio programming.

### **Receiving an Emergency Call**

When the radio receives an Emergency Call, an alert tone will be emitted.

"EMERGENCY" and the incoming P25 ID or MDC number or label will be displayed during the reception.

## **Messaging Options**

---

Digital Conventional P25 channels can be programmed to send and receive text messages and radio status messages.

Text messages can be selected from a pre-programmed list or manually entered using the virtual keypad on the HCH display.

Status messages are pre-programmed only.

Text Messaging can be enabled in the radio editor software.

### **Text Messaging [TXT]**

#### *Conventional Digital Channels*

Message types include predefined messages, manually entered messages or locally stored messages.

**Predefined Messages** - Predefined messages are programmed into the radio memory using the radio editor software.

**Manually Entered Messages** - Text messages can be manually entered via the virtual keypad on the HCH display. (Can only function by enabling OTAR/Data on each channel through PC Radio Editor software.)

**Locally Stored Messages** - Up to five manually entered messages can be stored in individual radios.

## **Storing Messages**

To store a manually entered text message, press the “TXT” button or select “Text Message” from the menu.

Select “Store” from the menu and press “Enter”.

Use the virtual keypad on the HCH display to enter the desired message and then press “Enter”.

Select the storage slot for the message and press “Enter” to store the message.

## **Sending a Text Message**

To send a text message, press “TXT” or select “Text Message” from the menu.

Select “Send” from the menu and press “Enter”.

### **Select Message Type**

From the “Select Entry Type” menu, choose the type of message to send and press “Enter”.

#### **Predefined List or Manual Entry List**

When “Predefined List” or “Manual Entry List” is selected, a list of available messages is displayed.

Select the message to be sent and press “Enter”.

## ***KNG HCH Operation***

NOTE: When sending a predefined message the message ID is transmitted. The receiving radio will display the message programmed with the corresponding ID. If the receiving radio has no programmed message with the transmitted ID, "Text Message X" is displayed, where "X" is the received ID number.

### **Manual Entry**

When "Manual Entry" is selected use the virtual keypad on the HCH display to enter the desired message. Press "Enter" to select the target radio.

### **Select Target Radio**

**Last Call** - Select "Last Call" to send the message to same radio you last sent a text message. Press "SEND" to send the message.

**Call List** - Selecting "Call List" opens a list aliases for pre-programmed Unit IDs. Select the desired target radio and press "Send" to send the message.

**Unit ID** - Select "Unit ID" to enter the P25 ID of the target radio. Use the keypad to enter the ID then press "Send" to send the message

**Broadcast** - Select "Broadcast" to send the text message to all text enabled radios regardless of unit ID. Press "Send" to send the message.

## **Message Acknowledgement**

When the text message has been received by the targeted radio, an alert tone will sound and the acknowledgment message will be displayed.

Press “OK” or wait for five seconds to return to normal radio operation.

If the targeted radio is unavailable, an alert tone will sound and the failed acknowledgement message will be displayed.

Press “RTRY” to resend the message.

Press “OK” or wait for five seconds to return to normal radio operation.

When sending a “Broadcast” message, no “text received” notification is shown. Only confirmation that the text has been broadcast will be displayed.

## **Receiving a Text Message**

When an incoming text message is received an alert tone is sounded and the "Text Message Received" message is momentarily displayed. The top programmed display line will alternate between the programmed setting and “Text Message” until the message is read.

### **Reading the message**

To read the message press the “TXT” button or select ‘Text Message’ from the menu.  
Select “Read” to view the message

### **Stored Messages**

Up to five messages can be programmed into the “Manual Entry List” and are accessed from the “Select Entry Type” menu.

### **User Status Messaging [STS]**

*Conventional Digital Channels*

#### **Sending a Status Update**

NOTE: When sending a message the message ID is transmitted. The receiving radio will display the message programmed with the corresponding ID. If the receiving radio has no programmed message with the transmitted ID “Status: Status X” is displayed, where “X” is the received ID number.

#### **Select Status Message**

Press the “STS” button or select “Status Update” from the menu.

From the “Select Status” menu, select the programmed message to send and press “Enter”.

### **Select Message Type**

From the “Select Target Type” select the type of message to be sent.

**Unit** - Send the message to an individual radio ID.

**Group** - Send message to a group of transceivers using the Talk Group ID.

**Dispatch** - Send the message to a dispatch console.

### **Unit Call**

Select Target Radio

**Last Call** - Select “Last Call” to send the message to the same radio you last sent a status message. Press “Send” to send the message.

**Call List** - Selecting “Call List” opens a list alias’ for the pre-programmed Unit IDs. Select the desired target radio and press “Send” to send the message.

**Unit ID** - Select “Unit ID” to enter the P25 ID of the target radio. Use the keypad to enter the ID then press “Send”.

**Group Call** - Selecting “Group” opens the menu to send a status message to a group of radios with the same talk group ID.

Select “Enter” to manually enter the ID or “Select” to choose an ID from the pre-programmed talk group pick list.

**Dispatch** - Select “Dispatch” to send a status message to a dispatch console.

## ***KNG HCH Operation***

### **Message Acknowledgement**

If the message has been received by the targeted radio, an alert tone will sound and the acknowledgment message will be displayed.

If the targeted radio is unavailable, an alert tone will sound and the failed acknowledgement message will be displayed.

Press “OK” or wait for five seconds to return to normal radio operation.

### **Receiving a Status Update**

When an incoming status update is received, an alert tone is sounded and the status message is momentarily displayed before returning to normal operation.

---

## Paging and Call Alert

---

### Conventional Two-Tone/DTMF/MDC1200 Paging [MUTE]

#### *Conventional Analog Channels*

The HCH can be programmed to receive two-tone, DTMF or MDC1200 pages on conventional analog channels.

#### **Receiving a page**

Select an analog or mixed-mode receive channel.

Turn on “Voice Mute” from the programmed button or menu item.

When voice mute is activated the  icon is displayed.

The radio ignores all voice traffic until the proper tone sequence is received.

When a proper signal is received the radio will emit an alert tone and allow the audio to pass.

If Auto Reset is programmed, the radio will return to the muted standby mode when the time conditions have been met.

### **Call Alert Paging [ALRT]**

#### *Digital Channels*

The HCH can be programmed to send and receive Call Alert messages on digital channels.

#### **Sending a Call Alert**

Press the “ALRT” button or open “Call Alert” from the menu.

#### **Select Target Radio**

##### **Last Call**

Select “Last Call” to send the message to the radio which you last sent or received a call alert. Press “Enter” to send the message.

##### **Call List**

Selecting “Call List” opens a list aliases for the pre-programmed Unit IDs. Select the desired target radio and press “Enter” to send the Call Alert.

##### **Enter ID**

Select “Enter ID” to enter the ID of the target radio.  
Use the keypad to enter the ID then press “Enter” to send the Call.

## **Receiving a Call Alert**

When a Call Alert is received, an alert tone will sound and the incoming unit ID or alias is displayed for approximately 5 seconds.

The top display line will alternate between the programmed display information and a Call Alert Received message.

Select “Call Alert” to reset.

## **Radio Check [RCHK]**

### *Conventional Digital Channels*

The HCH can be programmed to check the availability of a KNG radio with a specific P25 ID.

## **Requesting a Radio Check**

Press the “RCHK” button or open “Radio Check” from the menu.

## **Select Target Radio**

### **Last Call**

Select “Last Call” to send the request to the radio which you last sent a radio check request. Press “Enter” to send the query.

## ***KNG HCH Operation***

### **Call List**

Selecting "Call List" opens a list aliases for the pre-programmed Unit IDs.  
Select the desired target ID and press "Enter" to send the query.

### **Unit ID**

Select "Unit ID" to enter the P25 ID of the target radio.  
Use the keypad to enter the ID then press "Enter" to send the query.

If a successful handshake is performed, an alert tone will sound and the "Unit Available" message will be displayed for approximately five seconds.

If no validation is received from the targeted radio, an alert tone will sound and the "No Response" message will be displayed for approximately five seconds.

---

## Other Functions & Options

---

Many operational features and functions can be programmed for user selection and control. Items can be programmed as touch-screen buttons or to the two physical buttons (orange and black) located on the top panel of the control head.

In addition to these quick set buttons, a menu of multiple functions can be accessed with a "MENU" button.

This section covers the operation of user accessible functions.

### Backlight [LITE]

#### *Conventional and Trunked Channels*

The display lighting can be adjusted using the backlight function.

To adjust the display press the "LITE" button or select "Backlight" from the menu.

Select the desired setting:

**Auto** - The display brightness adjusts automatically with ambient conditions.

**Off** - Display and microphone lighting are all turned off. Touch the bottom area of the display to turn the display back on.

**Dim, Medium, Bright** - Sets to a fixed brightness.

## ***KNG HCH Operation***

### **Cloning**

#### ***Conventional Zones***

The Handheld Control Head can be set up to send or receive programmed information from other BK Radio products via a cloning cable available from BK Technologies.

Refer to the cloning cable instruction manual for cloning information between radios.

### **Control Lockout [LOCK]**

#### ***Conventional and Trunked Channels***

The Handheld Control Head offers two lockout settings, "Lock Keypad Only" and "Lock All Controls".

**Unlocked** - Disables Control Lockout on all touch screen and button operations.

**Lock Keypad Only** - Locks all touch screen and button operations except the three top buttons on the HCH.

**Lock All Controls** - Locks all functions programmed with the radio editor for lockout.

To enable the lock function press the "LOCK" button or select "Control Lock" from the menu.

Select the desired lockout setting and press "ENTER"

When attempting to access a locked function the HCH will display a message with instructions to disable Control Lock. The navigation wheel on the HCH front panel is used to unlock the controls.

To disable Control Lock press the left arrow button twice, then the right arrow button twice.

## **Global Positioning [GPS]**

*Conventional Digital Channels*

*Requires GPS Option KZA0589 or KAA0589.*

To access GPS functions press the "GPS" button or select "GPS" from the menu.

### **Viewing GPS information**

To view current coordinates open the GPS menu and select "GPS Information".

After acquisition, the current location is displayed in degrees, minutes and seconds.

### **Sending GPS information**

Depending on radio programming, GPS information is sent by a variety of triggers.

#### **PTT**

After a digital transmission, the GPS coordinates will be automatically transmitted.

#### **Periodic**

GPS coordinates are transmitted periodically using a programmed time.

#### **Emergency**

GPS coordinates are sent if the radio activates emergency.

#### **Power on/off**

GPS coordinates are sent once the radio powers up and acquires a position and also on power off.

## **User Request**

To send GPS information, open the GPS menu and select "Transmit Request".  
From the Request menu select the desired target ID and press "Enter".

## **Inhibit/Uninhibit [INH]/UINH]**

### *Conventional Digital Channels*

With "Inhibit" assigned to a button or menu function, a Handheld Control Head can temporarily disable other KNG radios using the targeted radio's unit ID number.

The disabled radio can only be re-enabled by sending an "Uninhibit" command.

NOTE: Inhibited radios cannot be read with the Neovision radio editor.

## **Sending a command**

To initiate an inhibit/uninhibit message, press the programmed button or select from the menu.

If prompted, use the virtual keypad to enter the User or Administrator password.

Press "ENTER" to open the menu.

## ***KNG HCH Operation***

### **Select Target Radio**

#### **Last Call**

Select “Last Call” to send the message to same radio you last sent an inhibit or uninhibit message. Press “SEND” to send the message.

#### **Call List**

Selecting “Call List” opens a list of alias’ from the pre-programmed Unit IDs. Select the desired target radio and press “SEND” to send the message.

#### **Enter ID**

Select “Enter ID” to enter the P25 ID of the target radio.  
Use the keypad to enter the ID and press “SEND” to send the message.

### **Message Acknowledgement**

When the message has been received by the targeted radio, an alert tone will sound and the acknowledgment message will be displayed.

Press “OK” or wait for three seconds to return to normal radio operation.

If the targeted radio is unavailable, an alert tone will sound and the failed acknowledgement message will be displayed.

Press “RTRY” to resend the message.

Press “OK” or wait for three seconds to return to normal radio operation.

## **Keypad Programming**

### *Conventional Systems, Zones and Channels*

Much of the information stored in the KNG mobile radio can be edited using the Handheld Control Head. Five separate programming functions can be enabled with the PC Radio Editor software.

Keypad programming selections can only be assigned as a menu item.

Open the menu as described in the Navigation section to select the information you want to edit.

Available programming functions are:

**Keypad** - Used to edit individual channel and zone information such as labels, frequencies, operating modes, etc.

**Call List** - Used to edit the P25 ID Call List entries.

**CxCSS Pick List** - Used to edit the list of user selectable Code Guard entries.

**NAC Pick List** - Used to edit the list of user selectable Network Access Codes.

**Talkgroup ID Pick List** - Used to edit the list of user selectable P25 Talk Groups.

*Refer to the Keypad Programming section for detailed information on how to edit programmed radio information.*

## ***KNG HCH Operation***

### **Monitor [MON]**

#### *Conventional Channels*

There are three settings available for monitoring traffic on a selected channel.

**Off** - Requires NAC or Tone.

**On** - Monitors activity on selected frequency regardless of NAC or Tone. 

**Open** - Open Squelch. 

If assigned as a Touch Screen or function button, press the button to toggle On/Off. Press and hold for Open Squelch.

When assigned as a menu item, open the menu as described in the Navigation section and select the Monitor mode you wish to use. Press "ENTER" to select.

### **Nuisance Channel Delete [NUIS]**

#### *Conventional and Trunked Channels*


Nuisance Channel Delete can be assigned as a touch screen item or to a top function button.

To temporarily remove a channel from the scan list, press the assigned button while the nuisance channel is being received.

The radio can be reverted to the programmed scan list by switching scan off and on, by cycling the radio power, or by changing the zone or channel.

## **Repeater Talkaround [T/A]**

### *Conventional Channels*

In Repeater Talkaround (T/A) mode, the radio will transmit on the programmed receive frequency of the selected channel. When T/A is enabled the  icon will be displayed on the top line of the LCD.

NOTE: Channels programmed as receive only are not affected by the Talkaround selection.

Talkaround selection can be assigned as a touch screen button, a menu list item, or to a top function button.

## **Squelch Adjust [SQL]**

### *Conventional Analog and Mixed Mode Channels*

Squelch Adjust is used to change the signal strength required for the Handheld Control Head's speaker to unmute on a per channel basis.

### **Adjust Chan Squelch**

Press the "SQL" button or select "Squelch Adjust" from the menu.

Select "Adjust Chan Squelch" from the menu.

Use the -/+ buttons to adjust the desired squelch level.

Press "ENTER" to set the level.

## **KNG HCH Operation**

### **Reset Squelch...**

Select "Reset Squelch" from the Squelch Adjust menu.

Select which channels to return to factory set squelch setting.

**Selected Channel** - Resets the selected channel.

**Selected Zone** - Resets all channels in the current operating zone.

**All Channels** - Resets all radio channels.

### **Surveillance Mode [SURV]**

*Conventional and Trunked Channels*

When Surveillance Mode is on, all audible indicators (beeps etc.) and lighting functions (LEDs and Display) are disabled. The LCD Touchscreen is set to the dimmest setting.

For best operation Surveillance Mode should be assigned as a touch screen button or on a top function button.

To enable or disable surveillance mode, press the assigned button.

### **Transmit Digital [TXD]**

*Conventional Mixed Mode Channels*

When Transmit Digital is on, channels programmed for selectable transmit mode will transmit in digital mode. When off, mixed-mode channels transmit in analog mode.

When transmitting in digital mode the display shows 'D' after the TX indicator. In analog transmit, 'A' will follow the indicator.

Transmit Digital selection can be assigned as a touch screen button, a menu list item, or to a top function button.

When assigned as a touch screen function, the "TXAD" button will be highlighted when in the Transmit Digital mode.

To switch the transmit mode on mixed mode channels press the "TXAD" button or select "Tx Digital" from the menu and choose "Analog" or "Digital".

## **Transmit Power [PWR]**

### *Conventional and Trunked Channels*

Transmit Power can be switched between the programmed high and low settings. The actual power output of the radio will depend on radio options settings, the radio model, and editor settings.

When operating in the high power mode, "H" will be displayed on the top line of the LCD. In low power mode, "L" is displayed.

To change the transmit power setting, press the "PWR" button or select "Tx Power" from the menu and choose "High" or "Low".

Press "ENTER" to set the selection.

### **Versions**

#### *Conventional and Trunked Channels*

Information about your Handheld Control Head can be viewed via the "Versions" menu item.

To review the information, open the Versions menu. Use the NEXT or PREV to view the installed revisions of individual items.

Version information includes:

**Release:** Overall release code.

**Software:** Release code for ARM.

**DSP:** Release code for DSP.

**File Format:** Currently installed file format.

**BSP:** Release code of installed BSP firmware.

**PCB Revision:** Installed printed circuit board revision number.

**Date of Manufacture:** Date of manufacture.

**FIPSCOM Bootloader:** Revision required for encryption installation.

**FIPSCOM Application:** Installed encryption source file.

Current version information can be found in the service section at [www.bktechnologies.com](http://www.bktechnologies.com).

## **Zone Select [ZONE]**

### *Conventional and Trunked Channels*

Zone Select allows the radio user to switch between programmed channel zones.

The Zone Select operation can be assigned to a touch screen button, a menu list item, or to a top function button.

When Zone is assigned to the touch screen or as a top function button, press the button to open the menu of available zones.

When assigned as a menu item, open the menu as described in the Navigation section.

Select the Zone you want to use.

Press "ENTER" select the Zone.

Also, If enabled, a zone can also be accessed directly from the touchscreen keypad.  
(Refer to your radio editor software documentation.)

(See also, Channel/Zone Selection Options.)

## **Keypad Programming Options**

---

### *Conventional Channels, Zones and Systems Only*

**NOTE:** Radio programming is to be performed only by authorized personnel. Any or all programmable functions are password protected to prevent unauthorized access.

Programmable categories include Individual P25 ID Quick Call/Receive List, User Tone List, User NAC List, User Talk Group ID List and Keypad Programming of Channel, Zone, Global and System parameters.

## **Entering Programming Mode**

Select "Keypad Programming" from the Menu List.

Enter the User or Administrator password at the prompt if required.

Select programming menu from the list of available options:

**Keypad** - Used for programming Channel, Zone, System and Global radio information including frequencies, labels, priority scan rate, etc.

**Call List** - Used to edit labels and P25 IDs in the stored User Call List.

**User Tones** - Used to edit the 32 User Selectable CTCSS/CDCSS tones list.

**User NACs** - Used to edit the 32 User Selectable NACs list.

**User TGIDs** - Used to edit the 32 User Selectable TGIDs list.

## **Keypad Programming**

Keypad programming consists of four sections:

**Global** - Settings that apply to all systems, zones and channels.

**System** - Applies to all conventional zone settings.

**Zone** - Settings that apply only to the selected zone.

**Channel** - Channel specific information such as frequencies, tones, etc.

## **Programming Global Parameters**

Programmable Global Parameters include:

Display Top Line

Display Top Line Alt

Display Middle Line

Display Mid Line Alt

Display Bottom Line

Display Bot Line Alt

User Password

Dual Speaker

Control Lockout

Disable HCH Speaker

HCH Master Vol Control

## ***KNG HCH Operation***

### **Displayed Information**

Information displayed on the three programmable display lines can be edited by selecting Top Line, Middle Line or Bottom Line from the Global menu.

Use the up/down buttons to select the desired displayed information for each line.

### **Alternating Display Information**

All three display lines can be programmed to alternate displayed information.

Alternating displayed information on the three programmable display lines can be edited by selecting Top Line Alt, Middle Line Alt or Bottom Line Alt from the Global menu.

### **User Password**

The User Password is used only for entering the keypad programming mode. The Administrator and Startup Passwords cannot be changed via the keypad.

Select "CLEAR" to reset the password to all zeros. Use the virtual keypad to enter a new six-digit password.

To edit individual digits select "EDIT". Use the Volume Select buttons to highlight the digit to change. Use the virtual keypad to enter a new digit.

Select "ENTER" to set the password and return to the previous step.

## **Dual Speaker**

When this option is on, audio is available on both the internal speaker and the speaker microphone speaker when attached.

## **Control Lockouts**

Control lock with the "Lock All Controls" selection can be edited from the "Control Lockouts" menu.

Use the +/- button to add or remove items from the lockout list.

Items selected for lockout will display the ☒ symbol.

## **Disable HCH Speaker**

Select "On" to disable the HCH Speaker.

## **HCH Master Vol Control**

Select "Off" to disable HCH Master Vol Control.

# **Programming System Parameters**

Programmable System Parameters include:

System Priority Channels

Transmit on Priority 1 selection

P25 ID

Scan Hold Time

### **System Priority 1 Channel**

A priority channel can be assigned on a system wide basis. If activated, a system priority channel will be monitored during priority scan regardless of the currently operating zone.

When set to "Off", Priority 1 <<2>> Channel assignment falls to Zone Priority 1 <<2>> setting. (See Programming Zone Parameters)

When set to "Use Main", the channel selected by the channel select buttons is the Priority 1 channel.

Choose "Select" to designate a specific channel as the System Priority 1 channel.

Use the Up/Down arrows to highlight the Zone of the desired Priority channel.  
Press "ENTER" to set the zone.

Use the Up/Down arrows to highlight the desired Priority channel. Press "ENTER" to finalize the selection.

### **Transmit on Priority 1**

If Transmit on Priority 1 is "On", the radio will transmit on the programmed Priority 1 channel whenever priority scan is turned on.

Use the Up/Down arrows to highlight the desired Operation. Press "ENTER" to finalize the selection.

## **System Priority 2 Channel**

A priority channel can be assigned on a system wide basis. If activated, a system priority channel will be monitored during priority scan regardless of the currently operation zone.

When set to "Off", the Priority 2 Channel is designated by the currently selected zone setting. (See Programming Zone Parameters)

When set to "Use Main", the channel selected by the channel select buttons is the Priority 2 channel.

Choose "Select" to designate a specific channel as the System Priority 2 channel.

Use the Up/Down arrows to highlight the Zone of the desired Priority channel.

Press "ENTER" to set the zone.

Use the Up/Down arrows to highlight the desired Priority channel.

Press "ENTER" to finalize the selection.

## ***KNG HCH Operation***

### **P25 Unit ID**

The radio's P25 ID can be edited by selecting "P25 Unit ID".

Select "EDIT" to edit the ID. Use the virtual keypad to enter the new ID.

### **Scan Hold Time**

The Scan Hold Time allows the user to hear responses to calls before the radio resumes scanning. It also allows time for the user to respond to a call when Talk Back Scan or Mixed Mode Talk Back is enabled. The options are from 0.0s to 7.5s in increments of 0.5s.


### **Programming Zone Parameters**

Select Add, Delete or Edit Zone from the Zone menu.


#### **Add Zone**

The option of adding a Standard Zone or a Command Zone is available. When selected, a new zone is added in the next available slot.

Example: If there are seven zones in the radio, the added zone will be zone eight



## Delete Zone



When selected the list of available zones is displayed.  
Choose the zone you wish to delete.

When a zone is removed all subsequent zones move up one spot.

Example: If there are seven zones in the radio and zone five is deleted, zone six now becomes zone five and zone seven becomes zone six.

## Edit Zone


Programmable Zone Parameters include:

Zone Label

Zone P1 Chan

Zone Tx on P1

Zone P2 Channel





## KNG HCH Operation


To edit zone parameters select "Zone" from the Keypad Programming menu.

Use the Up/Down arrows to select the zone to be programmed.

Press "ENTER" to open the Zone Parameters menu.



Select the desired parameter with the Up/Down arrows.  
Press "ENTER" to program the selection.



A screenshot of a control panel screen titled "Zone Label". Below the title, it displays "ZONE 1". At the bottom of the screen, there are two rectangular buttons labeled "ESC" and "EDIT". Below these buttons, the labels "VOL" and "CHAN" are positioned on the left and right sides respectively.

## **Zone Label**

To edit the zone label, select "EDIT". Use the virtual keypad to edit the zone label.

To edit individual digits use the Up Channel Select button and use the Down Channel Select button to delete a character.


Select "ENTER" to set the label and return to the previous step.

Use the Volume buttons to change character sets.

## **Zone Priority 1 Channel**

A priority channel can be assigned on a zone basis. If a system priority channel has been programmed, that channel will take precedence over the channel selected in the zone settings. (See "System Priority Channel")

When set to "Off", Priority 1 is ignored.



A screenshot of a control panel screen titled "Zone 1 P1 Channel". Below the title, it shows a list of options: "Off" (indicated by a right-pointing arrow), "Use Main", and "Select: Chan: 1". At the bottom of the screen, there are two rectangular buttons labeled "ESC" and "ENTER". Below these buttons, the labels "VOL" and "CHAN" are positioned on the left and right sides respectively.

## ***KNG HCH Operation***


### **Zone Priority 1 Channel (cont.)**

When set to "Use Main" the channel selected by the channel select button is the Priority 1 channel.

Choose "Select" to designate a specific channel as the Priority 1 channel.

Use the Up/Down arrows to highlight the desired Priority channel.

Press "ENTER" to finalize the selection.



### **Transmit on Priority 1**

If Transmit on Priority 1 is "On" the radio will transmit on the programmed Priority 1 channel whenever priority scan is turned on and that zone is active.

Use the Up/Down arrows to highlight the desired Operation.

Press "ENTER" to finalize the selection.

If a system priority channel has been programmed, that channel will take precedence over the channel selected in the zone settings. (See "System Priority Channel")

## **Zone Priority 2 Channel**

A priority channel can be assigned on a zone basis. If a system priority channel has been programmed, that channel will take precedence over the channel selected in the zone settings.. (See "System Priority Channel")

When set to "Off", Priority 2 is ignored.

When set to "Use Main" the channel selected by the channel select button is the Priority 2 channel.

Choose "Select" to designate a specific channel as the Priority 2 channel.

Use the Up/Down arrows to highlight the desired Priority channel.

Press "ENTER" to finalize the selection

Zone 1 P2 Channel

➡ Off  
Use Main  
Select: Chan: 1

ESCENTER

VOLCHAN

### Programming Channel Parameters

Select Zone

➡ 1: ZONE 1

2: ZONE 2

3: ZONE 3

4: ZONE 4

5: ZONE 5

6: ZONE 6

7: ZONE 7

8: ZONE 8

9: ZONE 9

10: ZONE 10

11: ZONE 11

12: ZONE 12

13: ZONE 13

ESC

ENTER

VOLCHAN

#### Add Channel


Select to add a new channel.

Choose the zone to which the channel is to be added.

Use the virtual keypad to enter a valid channel index number of 1-2048.

## Delete Channel

When selected, the list of programmed zones is displayed. Choose the zone of the channel you wish to delete. Then select the channel from the list.



## Edit Channel

Programmable Channel Parameters include:

- Channel Label
- Receive Frequency
- Receive Mode
- Receive CTCSS/CDCSS Tones
- Receive Network Access Codes
- Digital Squelch Mode
- Transmit Power
- Transmit Frequency
- Transmit Mode
- Transmit CTCSS/CDCSS Tones
- Transmit Network Access Codes
- Talkgroup ID

## KNG HCH Operation

Select Zone

➡ 1: ZONE 1

2: ZONE 2

3: ZONE 3

4: ZONE 4

5: ZONE 5

6: ZONE 6

7: ZONE 7

8: ZONE 8

9: ZONE 9

10: ZONE 10

11: ZONE 11

12: ZONE 12

13: ZONE 13

ESC

ENTER

VOL

CHAN

### Accessing Channel Parameters

To edit channel parameters select "Channel" from the Keypad Programming menu.

Use the Up/Down arrows to select the zone of the channel to be programmed.

Press "ENTER" to select the zone.

Use the Up/Down arrows to select the channel to be programmed.

Press "ENTER" to open the Channel Parameters Menu.

Select Channel

➡ 1: CHAN 0001

2: CHAN 0002

3: CHAN 0003

4: CHAN 0004

5: CHAN 0005

6: CHAN 0006

7: CHAN 0007

8: CHAN 0008

9: CHAN 0009

10: CHAN 0010

11: CHAN 0011

12: CHAN 0012

ESC

ENTER

VOL

CHAN

## Channel Label


To edit the channel label, select "EDIT". Use the virtual keypad to edit the channel label.

To edit individual characters, use the Up Channel Select button and use the Down Channel Select button to delete a character.

Select "ENTER" to set the label and return to the previous step.



The Channel Label screen displays the title "Channel Label" at the top. Below the title, the text "CHAN 0001" is shown. At the bottom of the screen, there are two buttons labeled "ESC" and "EDIT". The screen also features "VOL" and "CHAN" indicators at the bottom corners.



The Rx Frequency screen displays the title "Rx Frequency" at the top. Below the title, the text "151.62500 MHz" is shown. At the bottom of the screen, there are two buttons labeled "ESC" and "EDIT". The screen also features "VOL" and "CHAN" indicators at the bottom corners.

## Receive Frequency

To edit the frequency, select "EDIT". Use the virtual keypad to enter a new frequency.

To edit individual digits use the Up/Down Channel Select buttons to move the cursor.

Select "ENTER" to set the frequency and return to the previous step.


NOTE: Entering zero selects the lowest valid frequency for the model type.

## KNG HCH Operation

### Receive Mode

Use the arrow keys to select the desired mode.


Press "ENTER" to set the selection and return to the previous step.



### Receive CTCSS/CDCSS Code Guard

Receiver Code Guards only apply to analog or mixed mode operation. Code Guards can be subaudible tones or digital codes.

Select "Off" for analog signals to operate in carrier squelch mode.

**Receive CTCSS/CDCSS Code Guard (cont.)**

To enter a CTCSS tone, select "Tone" from the menu.

To edit the tone, select "EDIT". Use the virtual keypad to enter a new tone.

To edit individual digits use the Up/Down Channel Select buttons to move the cursor.


Select "ENTER" to set the tone and return to the previous step.

To enter a CDCSS value, select "Digital" from the menu.

To edit the tone, select "EDIT". Use the virtual keypad to enter a new code.

To edit individual digits use the Up Channel Select button and use the Down Channel Select button to delete a digit.

Select "ENTER" to set the tone and return to the previous step.



### Receive Network Access Code

Receiver NACs only apply to digital or mixed mode operation. NACs are programmed as three digit hexadecimal numbers. \$F7F is an invalid RX NAC.

The screen displays 'Rx NAC' at the top. Below it, the value '293' is shown. At the bottom, there are two buttons labeled 'ESC' and 'ENTER'. The screen also has 'VOL' and 'CHAN' indicators at the very bottom.

The screen displays 'Rx NAC' at the top. Below it, there is a prompt 'Enter: \$293' and a 'Select:' option. At the bottom, there are two buttons labeled 'ESC' and 'ENTER'. The screen also has 'VOL' and 'CHAN' indicators at the very bottom.

To program a NAC, select "ENTER".

To edit NAC value, select "EDIT". Use the virtual keypad to enter a new three digit value.

To edit individual digits use the Up Channel Select button and use the Down Channel Select button for navigation.

Select "ENTER" to set the NAC and return to the previous step.

**Receive Network Access Code (cont.)**

To select a NAC from the programmed picklist, choose "Select" from the menu.

Use the Up/Down arrows to highlight the desired NAC .

Select "ENTER" to set the NAC and return to the previous step.

Rx NAC	
➡ NAC-01	\$123
NAC-02	\$456
NAC-03	\$F73
NAC-04	\$000
NAC-05	\$000
NAC-06	\$000
NAC-07	\$000
NAC-08	\$000
NAC-09	\$000
NAC-10	\$000
NAC-11	\$000
NAC-12	\$000
NAC-13	\$000

ESC

ENTER

VOL

CHAN

**Squelch Mode**

Use the Up/Down arrows to select Normal or Selective. (Selective squelch is required for Individual Calls and use of Talkgroup IDs.)

Select "ENTER" to set the mode.

Squelch Mode	
➡ Selective	
Normal	

ESC

ENTER

VOL

CHAN

## KNG HCH Operation


### Analog Bandwidth

Bandwidth selection applies only to analog operation. Digital operation is always narrowband regardless of setting.

Use the Up/Down arrows to select Narrowband or Wideband.

Select "ENTER" to set the mode.

(Please see "Notice" on Page 2)



### Transmit Power


Individual channels can be designated to always transmit in low or high power.

Use the Up/Down arrows to select "Low" or "High" power.

Choosing "Selectable" allows the transmit power to be selected by a programmed Tx Power switch.

Select "ENTER" to set the mode.





## Transmit Frequency

To edit the frequency, select "EDIT". Use the virtual keypad to enter a new frequency.

To edit individual digits use the Up/Down Channel Select buttons to move the cursor.

Select "ENTER" to set the frequency and return to the previous step.

NOTE: Entering zero selects the lowest valid frequency for the model type.

## Transmit Mode

Use the Up/Down arrows to select the desired operating mode.



Press "ENTER" to set the selection and return to the previous step.



### Transmit CTCSS/CDCSS Code Guard

Transmit Code Guards only apply to analog or mixed mode operation. Code Guards can be subaudible tones or digital codes.

Select "Off" to transmit with no Code Guard tone.




To enter a CTCSS tone, select "Tone" from the menu.

To edit the tone, select "EDIT". Use the virtual keypad to enter a new tone.

To edit individual digits use the Up/Down Channel Select buttons to move the cursor.

Select "ENTER" to set the tone and return to the previous step.



### **Transmit CTCSS/CDCSS Code Guard (cont.)**

To enter a CDCSS value, select "Digital" from the menu.

To edit the tone, select "EDIT". Use the virtual keypad to enter a new code.


To edit individual digits use the Up/Down Channel Select buttons to move the cursor.

Select "ENTER" to set the tone and return to the previous step.

### **Transmit Network Access Code**

Transmitter NACs only apply to digital or mixed mode operation. NACs are programmed as three digit hexadecimal numbers.

\$F7E and \$F7F are invalid NACs.



## Transmit Network Access Code (cont.)

To program a NAC, select "ENTER".

To edit NAC value, select "EDIT". Use the virtual keypad to enter a new three digit value.

To edit individual digits use the Up/Down Channel Select buttons to move the cursor.

Tx NAC	
➡ NAC-01	\$123
NAC-02	\$456
NAC-03	\$F73
NAC-04	\$000
NAC-05	\$000
NAC-06	\$000
NAC-07	\$000
NAC-08	\$000
NAC-09	\$000
NAC-10	\$000
NAC-11	\$000
NAC-12	\$000
NAC-13	\$000

ESC

ENTER

VOL

CHAN

Select "ENTER" to set the NAC and return to the previous step.

To select a NAC from the programmed picklist, choose "Select" from the menu.

Use the Up/Down arrows to highlight the desired NAC .

Select "ENTER" to set the NAC and return to the previous step.


Tx NAC	
293	

ESC

EDIT

VOL

CHAN



## Talk Group ID

The Talk Group ID applies only to digital or mixed mode operation.


TGID can be programmed from 1 to 65535.

To program a TGID, select "ENTER".

To edit the TGID, select "EDIT". Use the virtual keypad to enter a new TGID.

To edit individual digits use the Up/Down Channel Select buttons to move the cursor. If the TGID uses a leading zero, it will be dropped when the TGID is displayed.

Select "ENTER" to set the TGID and return to the previous step.




## Talk Group ID (cont.)

To select a TGID from the programmed picklist, choose "Select" from the menu.

Use the Up/Down arrows to highlight the desired TGID .

Select "ENTER" to set the TGID and return to the previous step.



A screenshot of a handheld radio's menu screen. At the top, there is a list of three options: "1: Edit Call Entry", "2: Add Call Entry", and "3: Delete Call Entry". The first option is highlighted with a black background. At the bottom of the screen, there are two rectangular buttons labeled "ESC" and "ENTER". Below these buttons, the labels "VOL" and "CHAN" are visible on the left and right sides respectively.

## Call List Programming


To program the P25 Unit-to-Unit call list, select "Call List" from the Keypad programming menu.

Select Add, Delete or Edit Call Entry from the Call List menu.

### Add Call Entry


Select to add a new call entry. When selected, a new call entry is added in the next available slot and will be prompted to edit the call list will follow.

Example: If there are seven call entries in the radio, the added call entry will be call entry eight.



A screenshot of a handheld radio's menu screen titled "Tx NAC". It displays a list of 13 TGID entries, each with a number or code to its right. The first entry, "TGID-01", is highlighted with a black arrow pointing to it. At the bottom of the screen, there are two rectangular buttons labeled "ESC" and "ENTER". Below these buttons, the labels "VOL" and "CHAN" are visible on the left and right sides respectively.

Tx NAC	
TGID-01	1
TGID-02	2
TGID-03	\$F73
TGID-04	0
TGID-05	0
TGID-06	0
TGID-07	0
TGID-08	0
TGID-09	0
TGID-10	0
TGID-11	0
TGID-12	0
TGID-13	0



Call List

➡ 1: Unit 1  
2: Unit 2  
3: Unit 3  
4: Unit 4  
5: Unit 5  
6: Unit 6  
7: Unit 7  
8: Unit 8

ESC ENTER

VOL CHAN

## Delete Call Entry

When selected the list of available call entries is displayed. Choose the call entry you wish to delete.

When a call entry is removed all subsequent call entries move up one spot.

Example: If there are seven call entries in the radio and call entry five is deleted, call entry six now becomes call entry five and call entry seven becomes call entry six.



Edit Call

➡ Label: Unit 1  
Dest ID: 12

ESC ENTER

VOL CHAN

## Edit Call Entry

Select to edit existing call entry parameters.

Use the Up/Down arrows to select the call entry to be edited.


Select "ENTER" to select the item to open the item's programming window.

## Call Entry Label

To edit the Call Entry Label, select "EDIT". Use the virtual keypad to enter a new label.

To edit individual characters, use the Up/Down Channel Select buttons to move the cursor.

Select "ENTER" to set the label and return to the previous step.



## Call Entry ID

To edit the Call Entry ID, select "EDIT". Use the virtual keypad to enter a new ID.

To edit individual digits use the Up Channel Select button and use the Down Channel Select button to delete a digit.

Select "ENTER" to set the ID and return to the previous step.



User Tones	
➡ Tone-01	123.0 Hz
Tone-02	67.0 Hz
Tone-03	D023-
Tone-04	0.0 Hz
Tone-05	0.0 Hz
Tone-06	0.0 Hz
Tone-07	0.0 Hz
Tone-08	0.0 Hz
Tone-09	0.0 Hz
Tone-10	0.0 Hz
Tone-11	0.0 Hz
Tone-12	0.0 Hz
Tone-13	0.0 Hz

ESC

ENTER

VOL
CHAN

## Code Guard Picklist Programming

To program the User Selectable Code Guard List, select "User Tones" from the Keypad programming menu.

Use the Up/Down arrows to highlight the Code Guard to be programmed.

Press "ENTER" to select the item to open in the Code Guard menu.

User Tone 1	
➡ Tone:	123.0 Hz
Digital:	

ESC

ENTER

VOL
CHAN

To enter a CTCSS tone, select "Tone" from the menu.

To enter a CDCSS value, select "Digital" from the menu.

## CTCSS Tone

To enter a CTCSS tone, select "Tone" from the menu.

To edit the CTCSS tone, select "EDIT". Use the virtual keypad to enter a new frequency

To edit individual digits use the Up/Down Channel Select buttons to move the cursor.

Select "ENTER" to set the frequency and return to the previous step.

The screenshot shows a rectangular screen with a black border. At the top, the text "User Tone 1" is centered above a horizontal line. Below the line, the text "D000-" is centered. At the bottom of the screen, there are two rectangular buttons: "ESC" on the left and "EDIT" on the right. Below the "ESC" button is the label "VOL" and below the "EDIT" button is the label "CHAN".

## CDCSS Code

To enter a CDCSS code, select "Digital" from the menu.

To edit the CDCSS code, select "EDIT". Use the virtual keypad to enter a new three digit code.

To edit individual digits use the Up Channel Select button and use the Down Channel Select button to delete a digit.

Select "ENTER" to set the code and return to the previous step.

In this screen it is possible to invert a digital code guard - once that code guard has already been created (Choose the digits for the digital code guard, the "ENTER", then select it for editing. At this point the channel button becomes the "invert" button and is labeled "INV").

The screenshot shows a rectangular screen with a black border. At the top, the text "User Tone 1" is centered above a horizontal line. Below the line, the text "123.0 Hz" is centered. At the bottom of the screen, there are two rectangular buttons: "ESC" on the left and "EDIT" on the right. Below the "ESC" button is the label "VOL" and below the "EDIT" button is the label "CHAN".

User NAC	
➡ NAC-01	\$123
NAC-02	\$456
NAC-03	\$F73
NAC-04	\$000
NAC-05	\$000
NAC-06	\$000
NAC-07	\$000
NAC-08	\$000
NAC-09	\$000
NAC-10	\$000
NAC-11	\$000
NAC-12	\$000
NAC-13	\$000

ESC

ENTER

VOL
CHAN

## NAC Picklist Programming

To program the User Selectable NAC List, select "User NACs" from the Keypad programming menu. NACs are programmed as three digit hexadecimal numbers. \$F7E and \$F7F are invalid NACs.

Use the Up/Down arrows to highlight the NAC to be programmed.

Press "ENTER" to open the NAC editing screen.

To edit the NAC, select "EDIT". Use the virtual keypad to enter a new three digit value.

To edit individual digits use the Up/Down Channel Select buttons to move the cursor.

Select "ENTER" to set the NAC and return to the previous step.

User NAC 1
293

ESC

EDIT

VOL
CHAN

## Talkgroup ID Picklist Programming

To program the User Selectable TGID List, select "User TGIDs" from the Keypad programming menu.

Use the Up/Down arrows to highlight the TGID to be programmed.

Press "ENTER" to open the TGID editing screen.

User TGID 1

65535

ESC EDIT

VOL CHAN

To program a TGID, select "ENTER".

To edit the TGID, select "EDIT". Use the virtual keypad to enter a new TGID.

To edit individual digits use the Up/Down Channel Select buttons to move the cursor.

Select "ENTER" to set the TGID and return to the previous step.

User TGIDs

➔TGID-01	1
TGID-02	2
TGID-03	\$F73
TGID-04	0
TGID-05	0
TGID-06	0
TGID-07	0
TGID-08	0
TGID-09	0
TGID-10	0
TGID-11	0
TGID-12	0
TGID-13	0

ESC ENTER

VOL CHAN

## Notes:

---

---

---

---

---

---

---

---

---

---

---

**Notes:**

---

---

---

---

---

---

---

---

---

---

---

## Notes:

---

---

---

---

---

---

---

---

---

---

# INDEX

## **B**

Backlight.....	69
Bandwidth .....	95, 102
BSP .....	80
Busy Channel.....	29, 34

## **C**

Call List.....	60, 63, 66, 68, 74, 75, 82, 109
CHAN .....	18
Channel Label.....	15, 95, 97
Channel Scan.....	15, 17, 39, 40, 42, 45, 46
Channel Select.....	18, 27, 43, 81
Cloning .....	18, 70
Code Guard.....	17, 34, 35, 47, 53, 54, 75, 98, 99, 104, 105, 111
Controls.....	10, 70, 85
CxCSS .....	17, 54, 75

## **D**

DEL .....	19
DSP .....	80

DTMF .....	17, 65
------------	--------

## **E**

Emergency .....	11, 19, 57, 72
Encryption .....	17, 48, 53, 55, 80
Encryption Key.....	17, 48, 50, 55

## **F**

FCC .....	2
FIPSCOM.....	80

## **G**

GPS.....	19, 72
----------	--------

## **H**

Home.....	12, 19
Handheld Control Head Controls .....	10

## **I**

Industry Canada.....	6
----------------------	---

## **K**

Keypad Programming.....	19, 54, 75, 82, 83, 109
Keyset.....	20, 50, 52, 56

## **L**

LCD.....	11, 13, 23, 30, 39, 46
LED .....	6, 10, 11, 30
LITE.....	18, 69
Lockout.....	29, 34, 70, 85

## **M**

MENU.....	12, 18, 25
Menu Screen.....	25
Microphone Element.....	11
MON .....	19
Monitor .....	15, 19, 28, 34, 39, 76

## **N**

NAC.....	17, 18, 34, 54, 75, 82, 100
Narrowband.....	102
Navigation Wheel.....	24, 25, 71
Nuisance Channel.....	76

## **P**

P1 .....	14, 42, 91
P2 .....	14, 42, 91
PCB Revision.....	80
Picklist.....	19, 20, 34, 54, 55, 56, 111, 113
PRI .....	20
Priority.....	15, 20, 38, 42, 43, 44, 82, 85, 86, 87, 91-94
Priority Scan.....	14, 20, 39, 41-43, 46-47, 82, 86-87, 91
PSCN .....	20
PTT.....	6, 11, 29, 31, 34, 38, 41, 50, 72, 94
PWR .....	21

## **R**

Receive Frequency .....	77, 95, 97
Receive Mode .....	95, 98
Rekey .....	20, 49, 51
RKEY .....	20, 51
RXA.....	14
RXCG.....	19, 564
RXD.....	14
RXNAC.....	54

## **S**

SCAN .....	18
Scan Hold.....	85, 88
Scan List .....	18, 19, 22, 39-42, 45-47, 76
SCN+ .....	18
SEC .....	21
Secure .....	49
SQL .....	21
Squelch .....	21, 28, 35-36, 76-78, 95, 101
SURV .....	21
Surveillance .....	21, 78

## **I**

T/A .....	20
Tactical OTAR .....	52
Talkaround .....	15, 20, 77
Talkback Scan.....	38, 41, 47
Talk Group ID .....	16, 35, 53, 55, 63, 82, 107
TGID .....	17, 19, 35, 55, 82, 107, 114
Time-out Timer .....	29
Touch Screen .....	11, 13
Transmit Digital .....	79
Transmit Frequency .....	103
Transmit Mode .....	103
Transmit Power .....	14, 79, 102
TXA .....	14
TXAD.....	21, 79
TXCG .....	20, 54
TXD .....	14, 79
TXNAC .....	54

## **U**

UNIT .....	21
Unit Call.....	21, 63, 110
USB Port .....	10-11
User Password.....	83-84

## **V**

Versions .....	80
Vote Scan.....	45

## **W**

Wideband .....	102
----------------	-----

## **Z**

ZERO .....	22
Zeroize .....	22, 52
ZONE .....	22
Zone Scan.....	15, 22, 46-47
Zone Select.....	22, 27, 28, 44, 81

ZSC+ .....	22
ZSCN.....	22